



CWR137NGH N/Female to WR137 8 Hole Grooved Flange Coaxial to Waveguide Adapter 5.85-8.2 GHz

Rev 000

Electrical	
Frequency	5.85-8.2 GHz
VSWR	1.20
Impedance	50 Ohms
Mechanical	
N Interface per	MIL-STD-348B
Materials	
Body	Al
Body(N)	Passivated Stainless Steel
Contact	BeCu
Contact Plating	Au 50μ" Min
Dielectric	PTFE
ROHS Compliant	

